


**DRB-0090 DRAWBAR/PILOT KIT, COOLANT-THRU-SPINDLE SYSTEMS**


Machines fitted with Locking Drawbar mechanisms and Fadal Coolant-Thru-Spindle systems use this kit. The HDW-0195 Belleville Spring kit [ordered separately] is installed with DRB-0109 Sealing Washer at the bottom of the pocket.

Any DRB-0074 spacers that were previously installed underneath the Orientation Bridge legs **must be removed**.

The new DRB-0092 Knock-Out Cap is improved to allow the black tungsten carbide seal face to pivot better.


**HDW-0195 BELLEVILLES:**  
 Short Pocket: 4.325 inch [109.86 mm] is 38 Springs  
 Long Pocket: 4.627 Inch  
 [117.5 mm] is 42 Springs


**INSTALLATION OF DRB-0109 SEALING WASHER IN COOLANT-THRU SPINDLES**

1. Remove original Drawbar, and Belleville stack.
2. **Clean** sidewall in pocket so washer can seal against sidewall at bottom of pocket. A Brake Cylinder Hone could be helpful to do this.
3. Install HDW-0158 and HDW-0150 O'Rings onto DRB-0109 Sealing Washer *with DOW 111 grease*.
4. Insert Sealing Washer **SIDEWAYS** into opening [see photo].
5. Insert Drawbar up from bottom, and through hole in washer. Guide Drawbar through center O'Ring, and press Washer down to bottom of pocket.
6. This design washer allows Coolant-Thru fluid pressure to lift Sealing Washer without damaging O'Ring on bottom of the original design washer.

### DRB-0091 DRAWBAR/PILOT KIT, NON-COOLANT-THRU-SPINDLE SYSTEMS

Machines fitted with Locking Drawbar mechanisms and have no coolant-thru system use this kit. The HDW-0195 Belleville Spring kit [ordered separately] are installed with DRB-0068 Knock-Out Cap. The included DRB-0074 spacers are installed underneath the Orientation Bridge legs to raise the Bridge .070 inch.



### DRB-0030 DRAWBAR/PILOT KIT NON-LOCKING

Machines fitted with Non-Locking Drawbars in either 6500, 7500, 8000, 10000 or 15000 RPM configurations use this kit to replace Drawbar, with HDW-0195 [ordered separately] Belleville Springs. Use 47 springs if the manufacturing mark exists on the bottom of the long spindle key, and 44 if not marked.

